

# CAL PRE

## Ensuring memory for presentation



Move the cursor to a presentation number to select (the selected number is highlighted) and enter the presentation name. After the name is entered, [Capture] at the top right of the screen changes to [On] and the [=] symbol to the left of the presentation name appears highlighted. The preparation for screen capture is completed.



- When [Capture] is [On], screen data cannot be transferred to the FA-123. After pressing [F1] (SEL) to release the selected state, transfer screen data.

## 2. Capturing a screen image




While [Capture] is [On], enter each mode, display a screen to capture, and press [CTRL] + [F6]. Capturing of the screen is completed. When the screen returns to the CAL-PRE mode, the number next to the presentation name is increased according to the number of captured screens.



- Capturing of a screen is disabled while displaying Dynamic Graph, calculating, or drawing a graph.

## 3. Transferring a presentation file



To transfer the created presentation to the OHP model, select [Data Select] -> [CAL-PRE] in the communication mode and receive the presentation data by the OHP.

## 4. Making a presentation using the captured screens

Select a presentation(s) in the CAL-PRE mode and press [F6] (Play) or [EXE].

The screen stored in the CAL-PRE mode appears first, and then the screen switches to the next or previous page by pressing ▶ or ◀.